



Datasheet

ADS6134

Multizone Time of Flight Sensor

Version 1.2 | Aug 11, 2025

[Note]

Please be aware that most values written in the datasheet are in the **preliminary stages**.

As continual tests and improvements are being implemented, Adaps Photonics reserves the right to change any information without prior notice.

Introduction

Features & Benefits

- **High accuracy multizone detection ranging sensor**
 - Multizone ranging output with 4x4 separate zones.
 - Multitarget detection and distance measurement in each zone.
 - High accurate detection with long and short distance.

- **Fully integrated miniature module with an MCU**
 - Size: 5.0 mm x 3.0 mm x 1.3 mm.
 - Invisible light vertical cavity surface emitting 940nm laser (VCSEL) and integrated pulse laser driver.
 - 45°*45° FoV and 47°*47° FoI, using metalens on both transmitter and receiver.
 - Receiving array of single photon avalanche diodes (SPADs).
 - Low-power microcontroller running firmware.

- **Easy integration**
 - Single reflowable component.
 - I²C interface (up to 1MHz).
 - I²C communication interface is compatible with 1.2V, 1.8V and 3.3V.
 - Provide interrupt pin for frame ready event.
 - Flexible power supply options, 2.8V to 3.3V.
 - Works with many types of cover glass materials and compensate for smudge on glass.
 - Class 1 Eye Safety.



Description

ADS6134 is a direct time-of-flight (DToF), multizone ranging sensor, has up to 4x4 zones. Each zone has up to 3 objects. The sensor module is housed in a miniature reflowable package, integrating a SPAD array, physical infrared filters, and metalens. The sensor is based on SPAD, TDC and histogram technology. All processing of the raw data is performed on-chip and it provides distance information together with confidence values on its interface.

Applications

This sensor can be used in many applications including:

- Assist camera auto-focus, enhance the camera auto-focus (AF) system performance.

Improve camera performance in low light and low contrast scenes.

- Presence detection.
- Collision avoidance for robots.
- Keystone correction for video projectors.
- Gesture recognition.
- Distance measurement.
- IoT (User and object detection).
- Video focus tracking assistance.

1. ADS6134 Module Description

1.1. Block Diagram

The functional blocks of this device are shown below:




Figure 1-1 ADS6134 Block Diagram

1.2. Pin Diagram




Figure 1-2 ADS6134 Pin Diagram (TOP VIEW)

1.3. Pin Description

Table 1-1 Pin Description

Pin Number	Pin Name	Signal Type	Description
1	VDDC	Power Supply	Charge pump supply voltage, to be connected to main supply.
2	GNDC	Ground	Charge pump ground, connect all ground pins together.
3	NC	-	Don't connect.
4	INT	Output	Interrupt pin, high level voltage is the same with VCCIO. ⁽¹⁾
5	SCL	Input	I ² C clock input, high level voltage is the same with VCCIO. ⁽¹⁾
6	SDA	Input/Output	I ² C data, high level voltage is the same with VCCIO. ⁽¹⁾
7	VDD	Power Supply	Chip Supply voltage, to be connected to main supply.
8	NC	-	Don't connect.
9	EN	Input	Enable input active high, setting to low forces the device into shutdown and all memory content is lost. Connected to VDD if not used.
10	GPIO1	-	General purpose input/output, high level voltage is same with VDD, floating if not used.
11	GNDV	Ground	VCSEL Ground, connect all ground pins together.
12	VDDV	Power Supply	VCSEL Supply voltage, to be connected to main supply.

Note⁽¹⁾ : IO voltage of chip can be set 1.2V, 1.8V and 3.3V by IO_LVL_CFG register, it is recommended to keep same with the VCCIO.

2. Application Information

2.1. Application Schematic




Figure 2-1 ADS6134 Application Schematic

Note: INT, SDA and SCL pins should be pulled up.

2.2. PCB Layout Recommendation




Figure 2-2 ADS6134 PCB Layout Recommendation

Note: Bypass capacitors should be placed as close as possible to the supply and ground pins.

3. Electrical Characteristics

3.1. Absolute Maximum Ratings

Table 3-1 Electrical Parameters

Symbol	Parameter	Min.	Max.	Unit
VDDC, VDDV, VDD	Supply voltage to GND	-0.3	3.6	V
GNDC, GNDV	Ground	0	0	V
GPIO1	Floating	-0.3	3.6	V
INT	Digital I/O	-0.3	3.6	V
SCL	Digital I/O	-0.3	3.6	V
SDA	Digital I/O	-0.3	3.6	V
EN	Input	-0.3	3.6	V

3.2. Digital input and output

Table 3-2 Electrical Parameters

Symbol	Parameter	Min.	Typ.	Max.	Unit
GPIO1					
VIL	Low level input voltage	-0.3	-	0.3 * VDD	V
VIH	High level input voltage	0.7 * VDD		VDD	
VOL	Low level output voltage (I _{out} = 6mA)	-		0.4	
VOH	High level output voltage (I _{out} = 6mA)	0.8 * VDD		-	
IIL	Low level input leakage@ Vi = 0V	-0.15		0.15	uA
IIH	High level input leakage@ Vi=1.1*VCCIO	-10		10 ⁽¹⁾	
INT, SCL, SDA					
VIL	Low level input voltage	-0.3	-	0.3 * VCCIO	V
VIH	High level input voltage	0.7 * VCCIO		VCCIO	
VOL	Low level output voltage (I _{out} = 6mA)	-		0.4	
VOH	High level output voltage (I _{out} = 6mA)	0.8 * VCCIO		-	
IIL	Low level input leakage@ Vi = 0V	-0.15		0.15	uA
IIH	High level input leakage@ Vi=1.1*VCCIO	-10		10	
EN					
VIL	Low level input voltage	-0.3	-	0.3 * VCCIO	V
VIH	High level input voltage	0.7 * VCCIO		VCCIO	
IIL	Low level input leakage@ Vi = 0V	-0.15		0.15	uA
IIH	High level input leakage@ Vi=1.1*VCCIO	-10		10	

3.3. ESD

Electrostatic discharge

The ADS6134 module is compliant with electrostatic discharge (ESD) values presented in the table below.

Table 3-3 ESD Performance

Parameter	Specification	Condition
Human body model	ANS/ESDA/JEDEC JS-001-2023	± 2000V, 1500 Ohms, 100pF
Charged device model	ANSI/ESDA/JEDEC JS-002-2022	± 500 V

3.4. Temperature

Table 3-4 Temperature Ranges and Storage Conditions

Symbol	Parameter	Min.	Max.	Unit	Comments
T _{STRG}	Storage Temperature Range	-40	85	°C	
T _{BODY}	Package Body Temperature		260 °C (max)	°C	IPC / JEDEC J-STD-020 The reflow peak soldering temperature (body temperature) is specified according to IPC / JEDEC J-STD-020 "Moisture / Reflow Sensitivity Classification for Non-hermetic Solid State Surface Mount Devices."
RH _{NC}	Relative Humidity (non-condensing)		85	%	

3.5. MSL

Moisture sensitivity level

Moisture sensitivity level (MSL) is level 3 as described in IPC/JEDEC JSTD-020-C.

3.6. Typical Operating Conditions

Device parameters are guaranteed at nominal conditions unless otherwise noted. While the device is operational across the temperature range, functionality will vary with temperature.

Table 3-5 Operating Conditions

Symbol	Parameter	Min.	Typ.	Max.	Unit
VDDV, VDDC, VDD	Power Supply to GND	2.8	3.3	3.3	V
Temperature Range	Free-air temperature	-20	25	85	°C

3.7. Power Consumption

Table 3-6 Power consumption with typical condition

Mode	Typ.	Unit
HW Standby	2	uA
SW Standby	15.8	uA
Active Ranging	23	mA

3.8. Power Sequence

There are two options available for device power up/boot.

Option1: The EN pin is connected and controlled by host. HW standby is defined as the period when VDD is present and EN is low.




Figure 3-1 Power up and boot sequence (EN is controlled)

Option2: The EN pin is not controlled by host, it is tied to VDD through the pull-up resistor. In this case, the device goes to SW standby automatically after FW BOOT, without HW standby.




Figure 3-2 Power up and boot sequence (EN is not controlled)

3.9. State Machine

The diagram of the state machine is shown below:




Figure 3-3 State Machine

3.10. Interrupt Behavior and Ranging Timing

The INT pin is controlled by MCU, which level width and the polarity are configured by register. The interrupt will be active at the end of each frame and can be cleared by MCU after host get ranging data.




Figure 3-4 Interrupt Behavior and Timing

4. Communication Interfaces

4.1. I²C interface

The device is controlled by an I²C bus. It supports 7bits device addressing and standard mode (100Kbps), fast mode (400Kbps) and fast mode plus mode (1Mbps). Read and Write transactions comply with the standard I²C format.

The I²C interface uses two signals: serial data line (SDA) and serial clock line (SCL). Each device connected to the bus uses a unique address and a simple master/slave relationship exists.

Both SDA and SCL lines are connected to a positive supply voltage using pull-up resistors located on the host. Lines are only actively driven low. A high condition occurs when lines are floating, and the pull-up resistors pull lines up. When no data is transmitted, both lines are high.

Clock signal (SCL) generation is performed by the master device. The master device initiates data transfer. The I²C bus on the product device has a maximum speed of 1 Mbits/s.

During a write/read sequence, the 2nd~3rd byte received provides a 16-bit register address, which points to one of the internal 8-bit registers.

The I²C interface support 4 read/write operation:

- Single read
- Sequential read
- Single write
- Sequential write

4.1.1. Single Read

The host read data from a random address. The data format is as following.

S	Slave address[6:0]	0	A	Register address[15:8]	A	Register address[7:0]	A	Sr / P	Slave address[6:0]	1	A	Read data[7:0]	$\overline{A}$	P
---	--------------------	---	---	------------------------	---	-----------------------	---	--------	--------------------	---	---	----------------	----------------	---

4.1.2. Sequential Read

The host read data from the successive addresses, the data format is like the single read, the only difference is there are several read bytes before STOP asserted. The address will be incremented internally.

S	Slave address[6:0]	0	A	Register address[15:8]	A	Register address[7:0]	A	Sr / P	Slave address[6:0]	1	A	Read data[7:0]	A		Read data[7:0]	$\overline{A}$	P
---	--------------------	---	---	------------------------	---	-----------------------	---	--------	--------------------	---	---	----------------	---	--	----------------	----------------	---

N bytes of data, the register address incremented automatically

4.1.3. Single write

The host write data to a random address. The data format is as following.

S	Slave address[6:0]	0	A	Register address[15:8]	A	Register address[7:0]	A	Write data[7:0]	$\overline{A}$ / A	P
---	--------------------	---	---	------------------------	---	-----------------------	---	-----------------	--------------------	---

4.1.4. Sequential write

The host write data to the successive addresses, the data format is like the single write, the only difference is there are several write bytes before STOP asserted. The address will be incremented internally.

S	Slave address[6:0]	0	A	Register address[15:8]	A	Register address[7:0]	A	Write data[7:0]	A		Write data[7:0]	$\overline{A}$ / A	P
---	--------------------	---	---	------------------------	---	-----------------------	---	-----------------	---	--	-----------------	--------------------	---


N bytes of data, the register address incremented automatically

4.1.5. I²C device address

The default 7bit I²C device address is **0x19**. The address can be changed after power-up. Use the enable pin to enable only one device at a time to provide unique I²C device address.

4.2. Several ADS6134 on a single I²C bus

Several ADS6134 devices can share a single I²C bus if there are dedicated EN pad to each devices.



The procedure to initialize the devices to different I²C addresses is as follows:

1. Set EN1=0, EN2=0, EN3=0 (shutdown all devices),
2. Set EN1=1,
3. Download firmware patch to first ADS6134 device,
4. Reprogram I²C address for first device,
5. Set EN2=1,
6. Download firmware patch to second device,
7. Reprogram I²C address for second device,
8. Set EN3=1,
9. Download firmware patch to third device,
10. Reprogram I²C address for third device,
11. If there are further devices, repeat last three steps accordingly.

Note: I²C device address is stored in configuration register, it will be lost when power off, so must repeat the above steps when devices power on again.

4.3. I²C Timing Specification

The I²C Timing Specification is as shown.




Figure 4-1 I²C Timing Specification


Table 4-1 I²C Timing Specification

Symbol	Parameter	Standard Mode		Fast Mode		Fast Plus Mode		Unit
		Min.	Max.	Min.	Max.	Min.	Max.	
F _{SCL}	SCL clock frequency	0	100	0	400	0	1000	KHz
t _{HD,STA}	Hold time after (repeated) start condition. After this period, the first clock is generated.	4.0	-	0.6	-	0.26	-	us
t _{LOW}	Low period of the SCL clock	4.7	-	1.3	-	0.5	-	us
t _{HIGH}	HIGH period of the SCL clock	4.0	-	0.6	-	0.26	-	us
t _{SU,STA}	Set-up time for a repeated START condition	4.7	-	0.6	-	0.26	-	us
t _{HD,DAT}	Data in hold time	10	-	10	-	40	-	ns
t _{SU,DAT}	Data in setup time	250	-	100	-	50	-	ns
t _R	Rise time of both SDA and SCL signals	-	1000	-	300	-	120	ns
t _F	Fall time of both SDA and SCL signals	-	300	-	300	-	120	ns
t _{SU,STO}	Set-up time for STOP condition	4.0	-	0.6	-	0.26	-	us
t _{BUF}	Bus free time between STOP and START condition	4.7	-	1.3	-	0.5	-	us

5. Ranging Performances

5.1. Effective zone orientation

The figure below shows the zone definition in 4x4 mode. There are 16 zones in total which increment along a row first before starting a new row. The physical view is from the device top into the lens. The number of each zone, as indicated in the figure below, corresponds to the ZoneIDs returned by the sensor.



C = Corner Zones
Inner = All zones left

Figure 5-1 Zone mapping in 4x4 mode

5.2. Effective zone orientation

The ADS6134 module includes a metalens over the Rx aperture, which flips (horizontally and vertically) the captured image of the target. Consequently, the zone identified as zone 0 in the bottom left of the SPAD array, is illuminated by a target located at the top right-hand side of the scene. As shown in the following picture.




Figure 5-2 Effective orientation

5.3. Ranging Accuracy

1. Measurement conditions for dark:

- The full FoV (Filed of View) is covered by 45 degrees.
- Targets used are grey (17 % reflectance) and white (88 % reflectance).
- Normal voltage supply (3.3V) and temperature (23 °C).
- Indoor: No external light within the wavelength band 940nm, +/- 30nm.
- All tests are performed without cover glass.
- Range 200 mm~4800 mm.
- Typical samples used.

2. Measurement conditions for ambient light:

- The full FoV (Field of View) is covered by 45 degrees.
- Targets used are grey (17 % reflectance) and white (88 % reflectance).
- Normal voltage supply (3.3V) and temperature (23 °C).
- Tests are performed with 710 lux Halogen Lamp on (is equivalent to 5kLux sunlight).
- All tests are performed without cover glass.

Table 5-1 Summary of ADS6134 ranging performances.

Target reflectance (%)	Zone	Dark		Ambient light (5k Lux)	
		Max Distance	Accuracy	Max Distance	Accuracy
White 88 %	Inner	4800mm	±4%	600mm	±4%
	Corner	3800mm		500mm	
Grey 17 %	Inner	3400mm	±4%	700mm	±4%
	Corner	3000 mm		600 mm	

Note: IR light represents 5k sunlight equivalence, light on object only.




Figure 5-3 88 % White Card, inner and corner zone ranging performance




Figure 5-4 17 % Grey Card, inner and corner zone ranging performance

5.4. Micro Ranging Accuracy

Table 5-2 Summary of ADS6134 micro ranging performances.

Condition	Min.	Typ.	Max.	Unit
Min Distance	-	10	-	mm
Max Distance	-	300	-	mm
10-20mm	-5		+5	mm
20-100mm	-3		+3	mm
100-300mm	-5		+5	mm

6. Register Description

6.1. I²C_ADDR Register (Address 0x00)

Bit	Bit Name	Default	Access	Bit Description
7	Reserved	0	RW	Reserved.
6:0	I ² C_ADDR	0x19	RW	7bit I ² C address

6.2. CHIP_IDH Register (Address 0x01)

Bit	Bit Name	Default	Access	Bit Description
7:0	CHIP_IDH	0x17	R	The high byte of Chip ID.

6.3. CHIP_IDL Register (Address 0x02)

Bit	Bit Name	Default	Access	Bit Description
7:0	CHIP_IDH	0x0	R	The low byte of Chip ID.

6.4. PSN_H Register (Address 0x03)

Bit	Bit Name	Default	Access	Bit Description
7:0	PSN_H	0x61	R	The High byte of the product serial number.

6.5. PSN_L Register (Address 0x04)

Bit	Bit Name	Default	Access	Bit Description
7:0	PSN_L	0x34	R	The low byte of the product serial number.

6.6. CHIP_WORK Register (Address 0x05)

Bit	Bit Name	Default	Access	Bit Description
7:3	Reserved	0x0	R/W	Reserved
2	CHIP_SRST	0x0	W	If the bit is set to 1, chip is software reset.
1	FRM_END_INT	0x0	W	After the completion of one ranging frame, this bit is set to 1 to clear the interruption.
0	WORK_START	0x0	R/W	0: standby 1: ranging

6.7. INIT_STATE Register (Address 0x06)

Bit	Bit Name	Default	Access	Bit Description
7:6	CORE_WORK_MODE	0x3	R	00: deep sleep 01: sleep 10: reserved 11: active
5	FW_DL_DONE_RSTN_FLAG	0x0	R	0: core reset assert 1: core reset release
4	CHIP_RST_N	0x0	R	0: chip reset assert 1: chip reset release
3	GLB4_RST_N	0x0	R	0: internal reset assert 1: internal reset release
2	GLB3_RST_N	0x0	R	0: internal reset assert 1: internal reset release
1	GLB2_RST_N	0x0	R	0: internal reset assert 1: internal reset release
0	GLB_RST_N	0x0	R	0: internal reset assert 1: internal reset release

6.8. FW_CRC_VALH Register (Address 0x0F)

Bit	Bit Name	Default	Access	Bit Description
7:0	FW_CRC_VALH	0x0	R	The high byte of firmware CRC value.

6.9. FW_CRC_VALL Register (Address 0x10)

Bit	Bit Name	Default	Access	Bit Description
7:0	FW_CRC_VALL	0x0	R	The low byte of firmware CRC value.

6.10. IO_LVL_CFG Register (Address 0x13)

Bit	Bit Name	Default	Access	Bit Description
7:4	Reserved	0x0	R	Reserved
3	EN_SCHMG	0x0	R/W	0: initial Schmitt Trigger 1: general Schmitt Trigger
2	DEG_SEL	0x0	R/W	Reserved
1:0	IO_LVL	0x0	R/W	IO circuit supply voltage selection. Switching the IO level requires a wait of 120 μ s. 0: default (1.8V) 2: 2.8-3.3V 1: 1.2V 3: 1.8V

7. Package Information

7.1. package outline drawing

The ADS6134 module size is 5.0 mm x 3.0 mm x 1.3 mm. The package is reflowable component. The customer can integrate the ADS6134 in the system easily.




Figure 7-2 Package Outline Drawing




Figure 7-3 FoV/FoI Drawing

8. Lead-free solder reflow process

Table 8-1 Reflow Soldering

Reflow Soldering	
Pre-heat	150~200°C
Pre-heat time	Max. 120 seconds
Peak temperature	Max. 260°C
Soldering time	Max. 10 seconds (Max. 3 times)




Figure 8-1 Reflow Soldering

9. Laser Eye Safety

The ADS6134 contains a laser emitter and corresponding drive circuitry. The laser output is designed to remain within Class 1 laser safety limits under all reasonably foreseeable conditions including single faults in compliance with IEC 60825-1:2007 and IEC 60825-1:2014.

The laser output power must not be increased by any means and no optics should be used with the intention of focusing the laser beam.

Use of controls or adjustments or performance of procedures other than those specified herein may result in hazardous radiation exposure.



Figure 9-1 Class 1 laser label

10. Revision History

Table 10-1 Document revision history

Version	Date	Description
1.0	Oct. 18, 2024	Initial version
1.1	May 12, 2025	Update 5.4 Micro Ranging Accuracy
1.2	Aug.11, 2025	Updated 4.6&6.3 Typ. Voltage from 2.8V to 3.3V